

6502 OP-CODES ADRESSIERUNGS-MODI HEXADEZIMAL

	AC	IM	ZP	ZPX	ZPY	AB	ABX	ABY	IMP	R	INX	INY	IND	
ADC		69	65	75		6D	7D	79			61	71		ADC
AND		29	25	35		2D	3D	39			21	31		AND
ASL	0A		06	16		0E	1E							ASL
BCC										90				BCC
BCS										B0				BCS
BEQ										F0				BEQ
BIT			24			2C								BIT
BMI										30				BMI
BNE										D0				BNE
BPL										10				BPL
BRK									00					BRK
BVC										50				BVC
BVS										70				BVS
CLC									18					CLC
CLD									D8					CLD
CLI									58					CLI
CLV									B8					CLV
CMP		C9	C5	D5		CD	DD	D9			C1	D1		CMP
CPX		E0	E4			EC								CPX
CPY		C0	C4			CC								CPY
DEC			C6	D6		CE	DE							DEC
DEX									CA					DEX
DEY									88					DEY
EOR		49	45	55		4D	5D	59			41	51		EOR
INC			E6	F6		EE	FE							INC
INX									E8					INX
INY									C8					INY
JMP						4C							6C	JMP
JSR						20								JSR
LDA		A9	A5	B5		AD	BD	B9			A1	B1		LDA
LDX		A2	A6		B6	AE		BE						LDX
LDY		A0	A4	B4		AC	BC							LDY
LSR	4A		46	56		4E	5E							LSR
NOP									EA					NOP
ORA		09	05	15		0D	1D	19			01	11		ORA
PHA									48					PHA
PHP									08					PHP
PLA									68					PLA
PLP									28					PLP
ROL	2A		26	36		2E	3E							ROL
ROR	6A		66	76		6E	7E							ROR
RTI									40					RTI
RTS									60					RTS
SBC		E9	E5	F5		ED	FD	F9			E1	F1		SBC
SEC									38					SEC
SED									F8					SED
SEI									78					SEI
STA			85	95		8D	9D	99			81	91		STA
STX			86		96	8E								STX
STY			84	94		8C								STY
TAX									AA					TAX
TAY									A8					TAY
TSX									BA					TSX
TXA									8A					TXA
TXS									9A					TXS
TYA									98					TYA
	AC	IM	ZP	ZPX	ZPY	AB	ABX	ABY	IMP	R	INX	INY	IND	